

FCC NOTICE

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received,including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmfunterference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to nunications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.

 Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help Changes or modifications not expressly approved by Brother Industries, Ltd. could void the user's authority to operate the equipment.

Patent numbers and patent publication numbers which are related to this product are as below

USP4839742 USP4976558 USP5009530 USP5120147 USP4927278 USP4983058 USP5069557 USP5314256

GENERAL PRECAUTIONS

- . Use only Brother TZ tapes with this machine. Do not use tapes that do not have
- the 🍱 mark. Do not pull on the tape being fed from the P-touch, otherwise the tape cassette may be damaged
- Do not attempt to cut the tape while printing or feeding since this will damage the tape. . Do not clean the machine with alcohol or other organic solvents. Only use a soft, dry
- . Remove the batteries and disconnect the AC adapter if you do not intend to use the machine for an extended period of time.
- Note: If power is disconnected for more than three minutes, all text shown in the display and any text files stored in the memory will be lost. Language and unit settings will also be cleared
- Do not put any foreign objects into or heavy objects on the machine.
- . Do not expose the machine to extremely high temperatures or high humidity. Never leave it on the dashboard or in the back of your car.
- Avoid using the machine in extremely dusty places. Keep it out of both direct sunlight and rain.
- . Do not leave any rubber or vinyl on the machine for an extended period of time, otherwise the machine may be stained.
- Do not touch the print head mechanism. If the head is touched, clean it immediately
- with a soft wipe (e.g. a cotton swab) to avoid permanent damage · To avoid injuries, do not touch the cutter's edge
- . Use only the AC adapter designed exclusively for this machine. Use of any other adapter may void the warranty.

SPECIFICATIONS

LN6001001

Printed in China

4.32" (W) \times 7.84" (D) \times 2.2" (H)

(108mm (W) × 196mm (D) × 55mm (H)) 0.74 lbs. (335g) (without batteries and tape cassette) Power supply: Six AAA size alkaline batteries or optional AC adapter

(model AD-30) Brother TZ tape

1/4" / 3/8" / 1/2" (width) (6mm, 9mm, 12mm (width))

TC-5 (replacement)

POWER SUPPLY & TAPE CASSETTES


- Remove the back cover by pressing in the rough area at the top end of the machine and then flip away from the machine.
- If a tape cassette is already installed, remove it by pulling it straight up. Also, if batteries are already installed, remove them
- 2-1 Insert the batteries into the battery compartment with the positive end of the bottom three batteries pointing away from the cutter lever, and the positive end of the top
- three batteries pointing toward the tape cutter lever. Always replace all six batteries at the same time using brand new ones
- 2-2 Insert a tape cassette, making sure that it
- snaps into place. . Make sure that the end of the tape feeds under
- the tape guides. · Be sure to remove the paper tab when install-
- ing a new tape cassette · If the ink ribbon is loose, use your finger to
- wind the toothed wheel in the direction of the arrow on the cassette
- . Use only Brother TZ tapes with this machine
- Attach the back cover by inserting the two hooks at the bottom into the slots on the machine, then pushing down firmly on the cover until it snaps into place. After you have installed the tape, feed the tape (see FEEDING) once and then push in the tape cutter lever to cut the tape.

Optional AC adapter (model AD-30)


- Insert the plug on the adapter cord into the adapter jack on the bottom end of the
- Plug the other end of the adapter to the nearest standard electrical outlet.

Cutter unit (replacement)

If the cutter blade becomes blunt after repetitive use and the tape cannot be cut cleanly, replace with new cutter unit (stock no. TC-5) by obtaining from an authorized brother dealer.







GETTING STARTED

Start your machine

Supply power by using six AAA batteries or the optional AC adapter, and then press (b).

2 Set the language (English/French/German) 1.ENG? →

Choose a language with and press FRANÇAIS DEUTSCH ENGLISH

Check the display and press (4). (To cancel, press (3).)

Set the unit (mm/inch)

1 • m m ? → Choose a unit with and press

NOTE: • You can also display the languages and units by pressing the corresponding Num keys (1-3).

Check the display and press —. (To cancel, press 🖾.)

• The available accented characters depend on the language setting.

NOTE:

- To cancel operations, press To delete entries backward, press
- To initialize the settings, turn off the machine and then while holding down F and A, press to turn the machine back on. Finally, release (F) and (X)

MAKING TEXT

Switching UPPER CASE/LOWER CASE



Making A TWO LINE LABEL

Move the cursor to where the second line starts and press (4) NOTE: Use either 9 mm or 12 mm wide tape for two line labels

ABC#DEF_

Entering SYMBOLS



Group				Sym	bols	5			Group				Sym	bols	s		
Α	?	!	"	,	:	;	-	_	F	\rightarrow	←	1	\downarrow	Ŧ	D		
В	\	/	&	Ċ	i	~	§		G	۰	\$	£	€	¢	Fr	f	ij
С	@	#	%	B	©	тм			Н	ā	ō	В	μ	Đ	ð	Þ	þ
D	+	-	×	*	±	=	÷		I	a	*						
E	()	[]	<	>											
											_						

You can also display the symbols by pressing
 /

Setting LABEL LENGTH (AUTO/1.6" - 11.8")

You can also select the length by entering the length with Num keys.
To return to AUTO, press any alphabet key or .


To go to the next group, press [®].
To skip to a different group, press the corresponding character key of the group.
You can also scroll the symbols in each group by pressing the corresponding character

(F)+(8)

(F+0)


key of the group repeatedly


Entering ACCENTED CHARACTERS



- NOTE: You can also display the characters by pressing () • To go to the next letter group, press (<?...).
 - To skip to a different letter group, press the corresponding character key
 - · You can also scroll the characters in each letter group by pressing the corresponding character key repeatedly.

DESIGNING LABELS





J.SMITH っ・の∑−⊢ェ J.SMITH NOTE: • Two line texts are printed in NORMAL regardless of the setting.

Use clear tape in MIRROR, so the labels appear on the other side when stuck on glass

Setting UND	ERLINE/FRAME	(F+4)
F+F) (uḥūL/FŔĸÌ → (J	→F Nouni →
ABC BANNER ABC	MDL (Underline) ABC WOODEN	ABC NINE
NOTE: No underline of	or frame is set to texts in VERTICAL	style.
Setting TAB		(F+5)

You can make aligned texts by setting tabs. Example: To set a tab between "abc" and "d"

(abcd · · ·) ◆ (F) ◆ (F) (TAB · · · ·) ◆ (A) (abcud · · ·

NOTE: The cursor should be positioned where you set a tab

(F+6)**Setting TAB LENGTH** (0.0" - 4.0") F + F | Tậể LÊN + 4 + (7.2.5° · · · + 4) NOTE: You can also select the length by entering the length with Num keys

Length LCD Application **Application** VCR VHS 5.5" FILE TAB 2.7" 3.5" Floppy Disk AUDIO Audio Cassette CD CASE 3.9" VIDEO 8 VCR 8mm (Video 8) 3.6"

You can choose label length from six formats to create labels for various ap-

To CLEAR

Using AUTO FORMAT

All text and settings will be cleared. F + F | CLÉAR · · · +

PRINTING

TEXT PREVIEW

(F+B)

(F+-)

 $(F)+(\cdot)$

You can preview the text before printing. F + F P PRÉVIEW +

NOTE: • The LCD shows the whole text and the label length (mm/inch), then returns to the original Only the text can be previewed, but not the font, style, size, underline/frame or any addi-

FEEDING (TAPE FEED)

PRINTING

TAPE MARGIN



To cut off the label, push in the tape cutter lever on the upper-right corner of the machine.
 To prevent damage to the tape, do not try to cut while the message PRINT or FEED is

F + F | MARGIN + + + F | F | FULL + + + FULL/HALF/NARROW is for leaving equal margins on both sides of the text.

NOTE: Cut along the printed dots (:) with scissors so the text is centered in the label. HALF NARROW ABC ABC CHAIN is for printing more than 1 copy of a label with minimum margin <e.g. 1>. You can also create a label containing texts in various styles; print a text in one style, and before feeding, enter the second text in another style <e.g. 2>

FEED THE TAPE BEFORE USING THE CUTTER (see FEEDING/PRINTING). Otherwise A PART OF THE TEXT MAY BE CUT OFF. Do not try to pull the tape since this may NOTE: <e.g. 1>

ABC

Print Option/REPEAT PRINTING


windows or other transparent surfaces.

(F)+(J)

((F)+(,))

You can print up to 9 copies of each label.

ABC ABC ABC



 When the tape margin is set to CHAIN, FEED THE TAPE BEFORE USING THE CUTTER (see FEEDING/PRINTING). Otherwise A PART OF THE TEXT MAY BE CUT OFF. Do not try to pull the tape since this may damage the tape cassette.

When the tape margin is set to FULL/HALF/NARROW, cut along the printed dots (:) with scissors to separate the labels.

Print Option/NUMBERING

scissors to separate the labels.

ber by 1 after each label is printed. Example: To print copies of a label containing a serial number (0123, 0124 and 0125)

You can print many copies of the same text while increasing a selected num-

(123° · ·) → (F) → (F) (PRÎNT OP) → (J) → F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← F | ← **→** •


NOTE: • The last number that will be printed must be larger than the number selected in the text,

 The last full fine to the printed must be larger than the full between the least, otherwise the message ERROR appears.
 When the tape margin is set to CHAIN, FEED THE TAPE BEFORE USING THE CUTTER (see FEEDING/PRINTING). Otherwise A PART OF THE TEXT MAY BE CUT OFF. Do not try to pull the tape since this may damage the tape cassette.

When the tape margin is set to FULL/HALF/NARROW, cut along the printed dots (:) with

MEMORY (F+9)

You can store up to 9 frequently used text files and recall them to create labels more quickly and easily. (Total memory size: about 300 characters.)



When the memory is full, delete one or more files and then store the new file You can also choose a file number by pressing the corresponding Num key (1-9)

FUNCTION SHORTCUTS (F+...)

In addition to the basic steps to search for a function, PT-1000 provides you with function shortcuts so you can easily jump to a frequently used function just by pressing (F) and the shortcut key shown in the table below. To confirm, press (2) (or the shortcut key again).

Key	LCD message	Function	Key	LCD message	Function		
1	FONT	Character font		A/F	Auto Format		
2	SIZE	Character size	9	MEMORY	Memory		
3	STYLE	Print style	0	CLEAR	Clear text + style		
4	UNDL/FRM	Underline/Frame	0	MARGIN	Tape margin		
5	TAB	Tab setting	0	PRINT OP	Repeat/Numbering		
6	TAB LEN	Tab length	▣	PREVIEW	Text preview		
7	LENGTH	Label length	Θ	FEED	Tape feed		
NOTE DENIT OF A COLOR OF THE PROPERTY OF THE P							

NOTE:

• PRINT OP contains two functions, REPEAT PRINTING and NUMBERING.

• For PREVIEW and FEED, press

• to preview/feed after the LCD message appears

NOTE: You can also refer to the chart engraved on the back of the machine.

ERROR MESSAGE LIST

ERROR	An error occurred.			
BATTERY	The batteries are weak.			
BATIERY	The batteries are empty.			
FULL	The maximum number of characters (55 characters) have already been entered or the memory is full.			
LONG TXT	The text length exceeds the selected label length.			

TROUBLESHOOTING

Tiobiciii						
The display stays blank after you have turned on the machine.	Check that the batteries are correctly inserted. If the batteries are weak, replace them. Check that the adapter is correctly connected.					
The machine does not print, or the printed characters are blurred.	Check that the tape cassette has been inserted correctly. If the tape cassette is empty, replace it. Check that the character size is appropriate for the width of the tape that is used.					
The printed characters are not formed properly.	If the batteries are weak, replace them.					
Striped tape appears.	The tape cassette is empty. Replace it.					
The memory has cleared on its own.	The batteries may be weak. Replace them.					
A blank horizontal line appears through the printed label.	There may be some dust on the print head. Remove the tape cassette and use a dry cotton swab to gently wipe the print head with an up-and down motion.					
The machine has "locked up" (i.e., nothing happens when a key is pressed, even though the machine is on).	Turn off the machine, and then while holding down and machine back on. Finally, release and and the display and all text files stored in the memory are erased. Also, the language and unit settings will be cleared.					