



Affordable, dependable black & white laser output, and reliable home office performance

Monochrome Laser Printer

The Brother HL-L2405W is a simple, affordable choice for printing crisp single-sided documents with the convenience of wireless connectivity, all in a compact size.

- Printing up to 30ppm¹
- Flexible connectivity with dual band wireless module (2.4GHz / 5GHz), Wi-Fi Direct®, and USB interfaces.
- 250-sheet paper capacity, single sheet manual feed slot⁵
- Mobile device printing⁴
- Refresh EZ Print Subscription Ready

HL-L2405W

Monochrome Laser Printer

brother
at your side

Specifications:

| Print | |
|--|---|
| Print Technology | Electrophotographic Laser |
| Simplex Print Speed (max.) ¹ | Up to 30ppm |
| Time to First Page ² | Less than 8.5 seconds |
| Print Resolution (max.) | Up to 1200 x 1200 dpi |
| Print Emulations | GDI |
| Connectivity & Compatibility | |
| Standard Interfaces | Wireless 802.11b/g/n (2.4GHz) / 802.11a/n (5GHz), Hi-Speed USB 2.0 |
| Operating Systems Compatibility ³ | For the latest OS compatibility and to download drivers, visit support.brother.com. |
| Mobile Device Compatibility ⁴ | AirPrint®, Mopria™, Brother Mobile Connect, Wi-Fi Direct® |
| Alexa Print | Yes |
| Security | |
| Security Features | Enterprise Security (802.1x), TLS/SSL, IP Filter, SNMP v3, Setting Lock |
| Paper Handling | |
| Input Capacity (max.) ⁵ | 250-sheets standard tray, single-sheet manual feed slot |
| Output Capacity (max.) ⁵ | 100 sheets |
| Paper Size | Standard Tray: Letter, Legal, Executive, A4, A5, A6, B5, B6, Folio Manual Feed Slot: Width 3" to 8.5", Length 5" to 14" |
| Media Types | Standard Tray: Plain Paper, Thin Paper, Thick Paper, Recycled Paper Manual Feed Slot: Plain Paper, Thin Paper, Thick Paper, Recycled Paper, Bond, Label, Envelope (single) |
| Media Weights | Standard Tray: 16 to 43 lbs ⁶ Manual Feed Slot: 16 to 61 lbs |
| General | |
| Automatic Duplex Capability | No |
| Display | 1-line LCD |
| Processor | 600 MHz |
| Memory (std.) | 64 MB |
| Included Software ⁴ | Brother Mobile Connect for iOS® and Android™ Brother iPrint&Scan (desktop) for Windows and Mac® BRAdmin Light, BRAdmin Pro, Status Monitor ⁷ |
| Refresh EZ Print Subscription Eligible | Yes |
| Maximum Monthly Duty Cycle ⁸ | Up to 35,000 pages |
| Recommended Monthly Volume ⁹ | Up to 2,500 pages |
| Warranty | 1-year limited warranty |

Replacement Supplies & Optional Accessories:

brother
genuine

| | |
|-------------|--|
| TN830 | Standard Yield Toner Cartridge (1,200 pages) ¹⁰ |
| TN830XL | High Yield Toner Cartridge (3,000 pages) ¹⁰ |
| TN830V | Value High Yield Toner Cartridge (3,300 pages) ¹⁰ |
| TN830XL 2PK | Twin Pack of High Yield Black Toner Cartridges (3,000 pages per cartridge) ¹⁰ |
| DR830 | Drum Unit (15,000 pages) ¹¹ |

Dimensions / Weights:

| | |
|----------------------------|---|
| Unit Dimensions / Weight | 14.0" (W) x 14.2" (D) x 7.2" (H) / 15.1 lbs. |
| Carton Dimensions / Weight | 17.2" (W) x 11.1" (D) x 20.4" (H) / 17.5 lbs. |

Carton Contents:

Brother HL-L2405W, Starter Black Toner Cartridge (700 pages)¹⁰, DR830 Drum Unit (15,000 pages)¹¹, AC Power Cord, Product Safety Guide, Reference Guide, Warranty Card, Quick Setup Guide



At your side support. One-year limited warranty with free online, live chat, or phone technical assistance for the life of your product.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

COMPATIBLE WITH
WINDOWS



- Based on one sided printing. Change from default setting required.
- From ready mode and standard tray.
- For the latest OS compatibility and to download drivers, visit support.brother.com. Printing via macOS requires the use of AirPrint. Mac printer drivers are not provided.
- May require free download. Compatibility may vary by device and operating system. Requires connection to a wireless network.
- Maximum capacity based on using 20 lb. paper.
- Print speed may vary depending on size/type of paper used and paper source.
- Windows only
- Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

- The recommended range of monthly printed pages to achieve the best possible performance and printer life. Printers are intended to handle occasional usage beyond this range with little or no effect. Consistently printing above the recommended print volume, however, may adversely affect the print quality or life of the machine. It is always best to choose a printer with an appropriate recommended print volume to allow for any anticipated increase in printing needs.
- Approximate toner cartridge yields in accordance with ISO/IEC 19752 (Letter/A4).
- Approximately 15,000 pages based on 1 page per job (letter/A4 single-sided pages). The number of pages may be affected due to a variety of factors including but not limited to media type and media size.