DCP-L5510DN





Fast speeds, cost efficient output, and reliable business performance



Business Monochrome Laser All-in-One Printer

The Brother DCP-L5510DN is a great choice for busy offices and small workgroups that need cost-efficient printing, versatile paper handling, advanced security features, and reliable, high-quality output.

- Fast printing and copying up to 48ppm¹
- Cost-efficient output using 11,000-page replacement toner cartridge¹⁹. Includes 3,000-page toner cartridge¹⁷
- 50-page capacity auto document feeder¹² for multi-page copying and scanning
- Scan to popular destinations including cloud services⁸
- 350-sheet paper capacity¹², expandable up to 1,390 sheets¹⁹
- Gigabit Ethernet networking

DCP-L5510DN

Business Laser All-in-One Printer with Duplex Printing and Networking



Specifications:

opeoineationei		
Print		
Print Technology	Electrophotographic Laser	
Print Speed (max.) ¹	Up to 48ppm	
Time to First Page ²	Less than 6.7 seconds	
Print Resolution (max.)	tion (max.) Up to 1200 x 1200 dpi	
Print Emulations	PCL6, BR-Script3 ³ , IBM Proprinter XL, Epson FX-850, PDF Version 1.7, XPS Version 1.0	
Scan		
Scan Speeds (max) ⁴	Simplex: Up to 28ppm / 20ppm (black / color)	
Scan Resolution (max.)	Optical: Up to 1200 x 1200 dpi (doc glass); Interpolated ⁵ : Up to 19200 x 19200 dpi	
Scan To Capability	PC (Image, E-mail, OCR, File), Network Folder ⁵ , Email Server ⁶ , SharePoint, FTP, SSH Server (SFTP), USB Memory Stick ⁷ , Cloud Services (Web Connect) ⁸ , Mobile Devices ⁹ , Easy Scan to E-mail ¹⁰	
Advanced Scanning Features	Auto deskew, Blank page skip, Scan preview, File split, Multi-page to single-page, ID Scan, Scan profiles	
Сору		
Copy Speed / Copy Resolution (max.)	Up to 48ppm / Up to 1200 x 600dpi	
Copy Options	Sorting, N-in-1, Multi-copying (up to 999), ID copy, Reduce / Enlarge 25 - 400% in 1% increments	
Connectivity & Compatibili	ty	
Standard Interfaces	Gigabit Ethernet, Hi-Speed USB 2.0	
USB Host	Front: Print from and scan to USB memory stick; external card reader	
Operating Systems Compatibility ¹¹	For the latest OS compatibility and to download drivers, visit <u>support.brother.com</u> .	
Mobile Device Compatibility ⁹	AirPrint®, Mopria™, Brother Mobile Connect	
Cloud Services (Web Connect) ⁸	$\textbf{Google Drive}^{\intercal M}, \textbf{Evernote}^{\circledcirc}, \textbf{OneDrive}, \textbf{OneNote}, \textbf{Dropbox}, \textbf{Box}, \textbf{SharePoint Online}$	
Brother Cloud Apps¹0	Easy Scan to Email, Scan to Mobile, Cloud Secure Print, Fax Forward to Cloud or Email, Scan to Searchable PDF, Scan to Word, Scan to Excel, Scan to PowerPoint, Email Print	
Security		
Security Features	External Card Reader Compatibility, Active Directory, LDAP, Secure Function Lock, Enterprise Security (802.1x), Secure Print, TLS/SSL, IPSec, IP Filter, SMB v3, Syslog Reporting, SNMP v3, Secure BIOS, Password Intelligence, Lock Slot	
Paper Handling		
Paper Input Capacity (max.)12	250-sheet paper tray, 100-sheet multipurpose tray	
Optional Input Capacity (max.)12	1,390 sheets via optional trays	
Output Capacity (max.)12	150 sheets (face down), 1 sheet (face up)	
Document Glass Size	8.5" x 11" (Letter)	
Auto Document Feeder Capacity ¹²	50 pages	
Paper Size (max.)	Paper Tray: Letter, Legal, Executive, A4, A5, A6 Multipurpose Tray: 3.0" - 8.5" (W) / 5.0" - 14" (L)	
Media Types	Plain Paper, Letterhead, Colored Paper, Recycled Paper, Bond, Labels, Envelopes (up to 20)	
Media Weights ¹³	Standard Paper Tray: 16 to 43 lbs. Multipurpose Tray: 16 to 60 lbs. ADF: 17 to 24 lbs.	
General		
Automatic Duplex Capability	Print (default setting)	
Display	3.5" Color Touchscreen	
Customizable Shortcuts	48	
Processor	1.2 GHz	
Memory (std. / max.)	512MB / 512MB	
Included Software ¹⁴	Brother Mobile Connect for iOS® and Android™ Tungsten PaperPort™ 14SE with OCR for Windows Brother iPrint&Scan (desktop) for Windows and Mac®	
Optional Brother Value Added Services	Secure Print+, Custom UI, Remote Panel, Barcode Print+, Barcode Utility, ThinPrint Client Request Help, Order Supplies	
Optional Solutions	Tungsten ControlSuite, PaperCut, nddPrint, uniFLOW	
	11-1-00 000	
Maximum Monthly Duty Cycle ¹⁵	Up to 90,000 pages	
Maximum Monthly Duty Cycle ¹⁵ Recommended Monthly Volume ¹⁶	Up to 5,000 pages	

Replacement Supplies & Optional Accessories:

TN920	Standard Yield Toner Cartridge (3,000 pages) ¹⁷
TN920XL	High Yield Toner Cartridge (6,000 pages) ¹⁷
TN920V	Value High Yield Toner Cartridge (6,600 pages) ¹⁷
TN920XL 2PK	High Yield Toner Cartridge Twin-Pack (6,000 pages/Cartridge) ¹⁷
TN920XXL	Super High Yield Toner Cartridge (11,000 pages) ¹⁷
DR920	Drum Unit (45,000 pages) ¹⁸
LT-5505	Optional 250-Sheet Capacity Paper Tray ¹²
LT-6505	Optional 520-Sheet Capacity Paper Tray ¹²
CB-2000	Optional 15.7" Printer Cabinet / Stand

Dimensions / Weights:

Unit Dimensions / Weight	16.4" (W) x 18.1" (D) x 17.6" (H) / 36 lbs.
Carton Dimensions / Weight	21.6" (W) x 19.6" (D) x 22.8" (H) / 44 lbs.

Carton Contents:

Brother DCP-L5510DN, TN920 Toner Cartridge (3,000 pages)¹⁷, DR920 Drum Unit (45,000 pages)¹⁸, AC Power Cord, Quick Setup Guide



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.











- 1 Based on one-sided printing. Change from
- default setting required.
 From ready mode and standard tray.
 PostScript®3™ compatible.

- than 28 lb. paper. 14 May require free download. Compatibility may

- vary by device and operating system.

 15 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum prints life, it is back to change or prints.
- 2 From ready miode and standard tray.
 3 PostScript's™ compatible.
 4 Color and monochrome scan speeds in accordance with ISO/IEC 1799 with all advanced features turned off, using letter-sized apper at 200/300dpi.
 5 Windows only.
 6 Requires mail server support.
 7 PDF (up to ver. 1.7), JPE6, XPS files. Secure PDF / Signed PDF scan only.
 8 Requires an internet connection and an account with desired service.
 9 Requires an internet connection and an account with desired service.
 9 Requires an internet connection on a wireless network.
 10 Requires an internet connection.
 11 For the latest 0S compatibility and to download drivers, visit support, brothler com. Printing or scanning via mac0S requires the use of AirPrint. Mac drivers are not provided. For Windows and scanning; network connections support printing only.
 12 Maximum capacity based on using 20 lb, paper.
 13 Half speed and straight paper output with more than 28 lb, paper.
 14 Max results free drawnload . Comnatibility may
 15 Pagenium services and the connections of the connection of the co

 - size. 19 Requires additional purchase.